

WIREMOLD



Computer Grade Surge Protectors INSTALLATION INSTRUCTIONS

Installation Instruction No.: *INSPPR01R3* – Updated March 2007

Perma Power Computer Grade Surge Protectors from Wiremold / Legrand are available in impact resistant housings and in lengths up to 13 1/4" [337mm]. All Perma Power Computer Grade Surge Protectors are Listed or Recognized by Underwriters Laboratories under File No. E66421 and all 15A Units are CSA Certified under File No. LR62645. All units are in compliance with the National Electrical Code and the Canadian Electrical Code.

PERMA POWER®

Power Protection for Home/Office




TYPICAL INSTALLATION:

All Perma Power Computer Grade Surge Protectors from Wiremold / Legrand conform to and should be installed and properly grounded in compliance with requirements of the current National Electrical Code, Canadian Electrical Code or codes administered by local authorities. **CAUTION:** All electrical products may represent a possible shock or fire hazard if improperly installed or used. Do not plug into another relocatable power tap. The 3-prong, grounding type plugs in all units are for use with 3-prong, grounded receptacles only. Modifying or bypassing the ground pin for use in a non-grounded receptacle or plugging into another relocatable power tap may lead to electrical shock, is not recommended and voids the product warranty. All units are designed for interior use in dry locations only. Check all local and national electrical codes for proper installation.

MOUNTING INSTRUCTIONS:


SNAP-ON/SLIDE-OFF:

Screw mounting clips into mounting surface on a straight line. Measure 1" [25mm] in from each end of the unit. Place unit's mounting rails in one side of mounting clips and snap in position so unit is flush with mounting surface. To remove unit, simply slide it out of clips.




KEYHOLE MOUNTING:

Measure distance from center of keyhole slots. Mark this distance on the surface to be mounted. Install mounting screws into surface. Leave screw head about 1/8" [3mm] above surface. Place unit over screws. Slide unit left, right or down to secure it in position.



PHONE/FAX/DATA LINES:

Install surge protector according to instructions above. Insert one end of the 6' [1.8m] phone/fax/data cord (provided) into wall jack. Insert other end into the "LINE INPUT" jack on the surge protector. Insert one end of the phone/fax/data cord, from the equipment to be protected, into the "LINE OUTPUT" jack on the surge protector. Insert the other end into the appropriate jack on the equipment.



About your Perma Power Product: Each unit is 100% tested prior to packaging. All Surge Suppressors feature electrical and mechanical grounding and a resettable circuit breaker for overload protection. All units are rated 15 Amps, 120 volts, 60 Hz.

About your Surge Protector: Perma Power surge protectors are designed to protect electronic equipment from the destructive effects of surges, spikes and noise. However, a surge protector is not a lightning arrester and does not protect equipment in the rare instance that lightning actually strikes the building service entrance or antenna. All surge suppressors feature a surge indicator light which indicates that the unit is operating at full protection.

Troubleshooting: If you are receiving no power to your Perma Power product, first make sure the unit is plugged firmly into your wall outlet. Plug the unit into a different wall outlet to verify the condition. If there is still no power, the built-in circuit breaker may need to be reset. If you are still having problems, please call technical support at **1-800-736-8739**.

Surge Protector Warranty Information:

PERMA POWER®

Power Protection for Home/Office

All Perma Power Computer Grade Plug-In Surge Protectors offer a Five-Year Product Warranty and \$10,000 Connected Equipment Warranty.

Wiremold / Legrand will repair or replace, at our discretion, any Perma Power plug-in surge protector which proves to be defective up to five years from the date of purchase. In addition, Wiremold / Legrand will reimburse the original owner of a registered Perma Power Computer Grade Surge Protector for damage caused to any properly connected equipment by an AC surge if the surge protector is found to be at fault, up to a maximum of \$10,000.*

All Perma Power Computer Grade Rack Mount Surge Protectors offer a Five-Year Product Warranty. Wiremold / Legrand will repair or replace, at our discretion, any Perma Power Computer Grade Rack Mount Surge Protector which proves to be defective up to five years from the date of purchase.

*Consult enclosed Warranty Card for complete details.

WIREMOLD



Wiremold / Legrand

U.S. and International:

60 Woodlawn Street • West Hartford, CT 06110

1-800-621-0049 • FAX 860-232-2062 • Outside U.S. 860-233-6251

Canada:

570 Applewood Crescent • Vaughan, Ontario L4K 4B4

1-800-723-5175 • FAX 905-738-9721

