

Catalog Numbers • Les Numéros de Catalogue • Los Números de Catálogo: RACCESS-R

Country of Origin: Made in U.S.A • Pays d'origine: Fabriqué en Etats-Unis • País de origen: Hecho en Estados Unidos de America

DESCRIPTION

The Wattstopper RACCESS-R Cell Modem Kit includes a dedicated 4G LTE modem that is pre-activated for cellular use and pre-configured out of the box to enable secure remote access. No device configuration is required.

Once installation is complete, contact the Remote Operations Center (ROC) at 888-740-7950 to verify signal strength of the modem.



INSTALLATION PROCESS FOR WATTSTOPPER DLM SYSTEMS

The following instructions are for installing a Cell Modem Kit into a DLM enclosure for DLM networked systems containing a LMJA-x125 or LMJA-x300 Network Controller.

Prepare Enclosure

1. Disconnect power from the enclosure.
2. **For the LMNC-ENC1 enclosure:** Remove knockout on lower left side of enclosure.
For the LMNC-xx enclosure: Drill a 1" OD hole in the lower left side of enclosure. Recommended location is 2" up from bottom of enclosure and 4.25" measured from the back of the enclosure.
Warning—Remove all metal drill filings from inside enclosure, to prevent any filings from contacting any electronics within the cabinet, before continuing to next step
3. Insert rubber grommet into hole.

Mount antenna


Enclosure Mounted (Preferred method)

The antenna may be mounted to the top or bottom of the enclosure. The orientation of the antenna must be vertical as shown on page 3. The base of the antenna is magnetic, no additional mounting hardware is necessary.

Remote Antenna Mounting

The antenna can be mounted away from the enclosure in situations where 1.) space does not allow for mounting vertically on the enclosure, or 2.) as a means to improve signal quality. The antenna comes with a 12.5 foot cable and the magnetic base will adhere to any ferrous metal surface. An 8 foot extension cable is also available.

For additional antenna mounting options, the Extended Antenna Kit (RACCESS-ANTKIT) may be purchased separately.



Extended Antenna

Install Cellular Modem

The cellular modem is shipped with a hook and loop adhesive fastener for easy installation to the inside bottom surface of the enclosure.


Warning—Before mounting modem, clean the enclosure surface with Isopropyl alcohol.

NOTE: The modem ships with optional mounting bracket and additional antennas that are not required for standard installation described in this instruction. Do **not** use these antennas if the modem is installed inside the cabinet.

NOTE: Wi-fi is disabled for security purposes.

Remove the backing from the adhesive side of the fastener. Position the modem so the RJ45 Ethernet ports are facing the right side of the enclosure. Press modem firmly to bottom surface of enclosure for 15 seconds.

Modem Connectors



Connect the Antenna

Pass the antenna cable through the grommet hole into the enclosure. With the end of the cable inside the enclosure, connect each SMA antenna connector to the Cellular Modem SMA connectors. It doesn't matter which end goes to which connector. Do not over tighten with tools. Coil and tie wrap any excess cable length within the enclosure being careful not to kink the cable.

Connect Power to Modem

Plug power supply into electrical outlet inside the enclosure.


Connect power supply to modem.

Ensure power is switched on, using the power switch on the front panel of the modem. The Power LED will light.

Connect Modem to DLM Network


If Using an LMNC-ENC-1

Connect an ethernet cable from the left port of the modem to the left port (labeled SEC) of the LMJA-xxx, or a switch if using.




If Using an LMNC-xx

Connect an ethernet cable from the left port of the modem to any available switch port.




Apply Connected Services Sticker


Locate Wattstopper Connected Services sticker and apply to the front lower left corner of the enclosure door.



This completes the installation; your modem should now be activated. Please remember to **call the ROC** at this point to confirm the modem has good signal strength.



LMNC-ENC1 with RACCESS-R kit components installed



LMNC with RACCESS-R kit components installed

INSTALLATION PROCESS FOR WATTSTOPPER PLUS SYSTEMS

Mount antenna


Enclosure or Server Rack Mounted (Preferred method)

The antenna may be mounted to the top or bottom of an enclosure or server rack. The orientation of the antenna must be vertical as shown below. The base of the antenna is magnetic, no additional mounting hardware is necessary.

Remote Antenna Mounting

The antenna can be mounted away from the enclosure in situations where 1.) space does not allow for mounting vertically on the enclosure, or 2.) as a means to improve signal quality. The antenna comes with a 12.5 foot cable and the magnetic base will adhere to any ferrous metal surface. An 8 foot extension cable is also available.

For additional antenna mounting options, the Extended Antenna Kit (RACCESS-ANTKIT) may be purchased separately.



Extended Antenna

Mount the cellular modem

Use the modem's built-in mounting holes to mount the modem to the wall somewhere near the IP switch using the provided screws.

Connect the antenna.

Connect the SMA antenna connector to the Cellular Modem SMA connector. It doesn't matter which end goes to which connector. Do not over tighten with tools. Coil and tie wrap any excess cable length, being careful not to kink the cable.

Connect Power to Modem

Plug power supply into electrical outlet in an electrical outlet near the system setup.


Connect power supply to modem.

Ensure power is switched on, using the power switch on the front panel of the modem. The Power LED will light.


Connect modem to PLUS network

Use an Ethernet cable to connect the modem to any available switch port. The IP switch should be connected to port 2 (172.24.172x network) of the SSU/SSU-LITE unit.

If using an SSU




If using an SSU-LITE



Apply Connected Services Sticker

Locate Wattstopper Connected Services sticker and apply to the top of the modem.



This completes the installation; your modem should now be activated. Please remember to **call the ROC** at this point to confirm the modem has good signal strength.

WARRANTY INFORMATION

Wattstopper warrants its products to be free of defects in materials and workmanship for a period of one (1) years. There are no obligations or liabilities on the part of Wattstopper for consequential damages arising out of, or in connection with, the use or performance of this product or other indirect damages with respect to loss of property, revenue or profit, or cost of removal, installation or reinstallation.

INFORMATIONS RELATIVES À LA GARANTIE

Wattstopper garantit que ses produits sont exempts de défauts de matériaux et de fabrication pour une période de un (1) ans. Wattstopper ne peut être tenu responsable de tout dommage consécutif causé par ou lié à l'utilisation ou à la performance de ce produit ou tout autre dommage indirect lié à la perte de propriété, de revenus, ou de profits, ou aux coûts d'enlèvement, d'installation ou de réinstallation.

INFORMACIÓN DE LA GARANTÍA

Wattstopper garantiza que sus productos están libres de defectos en materiales y mano de obra por un período de un (1) año. No existen obligaciones ni responsabilidades por parte de Wattstopper por daños consecuentes que se deriven o estén relacionados con el uso o el rendimiento de este producto u otros daños indirectos con respecto a la pérdida de propiedad, renta o ganancias, o al costo de extracción, instalación o reinstalación.