

20A GFCI works with the existing three-wire PlugTail connectors creating a non-feed thru application for facility owners. At rough-in, just install the same right-angle connector for GFCI and receptacle openings. PlugTail® devices and connectors mean that device installation is the same regardless of skill level of the installer. The UL-Listed connectors are keyed to ensure proper wiring installation into each receptacle.

## Features & Benefits

Conducts an automatic test every three seconds, ensuring it's always ready to protect. If the device fails the test, the indicator light flashes to signal that the GFCI should be replaced. It also has our proven SafeLock® Protection feature: if critical components are damaged and protection is lost, power to the receptacle is disconnected

Faster, more reliable installation

No exposed terminals create a finger-safe application before, during, and after installation

Built-in connector features large brass terminal blades to ensure consistent, reliable electrical connections to PlugTail Connector

GFCI works with the existing 3-wire PlugTail connectors creating a non-feed-through application for facility

Zinc-plated steel mounting strap

## **Specifications**

Pass & Seymour	Color	Red
China	Number of Receptacles	2
Commercial, GFCI, Indoor, Self-Test	Application Sector	Residential/Commercial
ULus, UL Listed, FSUL	Warranty Type	1-Year Limited Warranty
Outlet		
.72 in	Product Depth US	1.2 in
.2 in		
)	hina  ommercial, GFCI, Indoor, Self-Test  JLus, UL Listed, FSUL  utlet	hina Number of Receptacles  ommercial, GFCI, Indoor, Self-Test Application Sector  ULus, UL Listed, FSUL Warranty Type  utlet  72 in Product Depth US

## Listing Agencies / 3rd Party Agencies

cULus Listed	Yes		
Technical Information			
Interrupt Rating	4 A	Frequency Rating	60 Hz
Trip Range	5±1 mA	Connection	Built-in Connector
Amperage	20 A	Number of Poles	Double Pole
Indoor/Outdoor	Indoor	Voltage	125.0 V
Environmental Conditions	95% Humidity, UL 94 V2		