# La legrand®



radiant Collection radiant® 4-Button Digital Timer, Dark Bronze Part No. RT2DBCCV4

Installs easily in place of a standard light or fan switch, or older spring-wound timer and includes manual on/off through the paddle switch for added convenience. A locator light illuminates when switch is off, emitting a soft glow to help you find it in the dark. Made exclusively for use with screwless Wall Plates from the radiant® Collection, sold separately.

## Features & Benefits

| Works with a variety of light bulbs or fixtures, including: Incandescent, LED, fluorescent, compact fluorescent (CFL), magnetic low-voltage (MLV) and electronic low-voltage (ELV), 1/6 hp. | Automates control of lights for energy and cost<br>savings. Also includes manual on/off through the<br>paddle switch for added convenience. |
|---|---|
| Lets you select a desired preset shut-off time, including 60, 40, 20 and 10 minutes.  | Installs easily in place of a standard light or fan switch, or older spring-wound timer.  |
| Locator light illuminates when switch is off, emitting a soft glow to help you find it in the dark.   | More color options available to fit any style.  |
| Complete the look with a sleek, screwless radiant® Wall Plate, and coordinate with other designer switches and outlets available from the   |   |

## Specifications

radiant® Collection.

#### General Info

| Product Line       | Pass & Seymour | Replaced by Part Number |                        |
|--------------------|----------------|-------------------------|------------------------|
| Color              | Dark Bronze    | Country Of Origin       | China                  |
| Features           | Timer          | Switch Type             | Paddle                 |
| Number of Switches | 1              | Application Sector      | Residential/Commercial |
| Standard           | cULus          | Warranty Type           | 5-Year                 |
| Туре               | Switch         |                         |                        |
|                    |                |                         |                        |

#### Technical Information

| Connection        | Back & Side Wired | Coil Voltage    | 120 V         |
|-------------------|-------------------|-----------------|---------------|
| Contact Rating    | 600Watts          | Number of Gangs | 1             |
| Number of Buttons | 4                 | Amperage        | 15 A          |
| Action            | Single Pole       | Number of Poles | Single Pole   |
| Indoor/Outdoor    | Indoor            | Timing Range    | 10-60 minutes |
| Wattage           | 600 W             | Mounting Type   | Box           |
| Voltage           | 120.0 V           |                 |               |