

**Overview**

The new *Equinox App™*, is Vantage's exclusive, industry revolutionizing, approach to whole-home control using your existing Android™ and/or iOS™ tablets and smart phones. The exact, same *Equinox App* is used in Vantage's new Equinox 73™ in-wall touchscreen; so, when switching devices, iPhone® to iPad® to Android tablet to Android smart phone, back to in-wall touchscreen, etc., the *learning curve* is eliminated. Widgets are displayed in a dashboard arrangement providing effortless control and feedback status of the Vantage System. Each widget's content has been carefully created to provide the most common interface controls. Widgets are self discovering, eliminate countless hours of tedious programming. Enjoy easy navigation and control, with *real-time* feedback, of lighting, audio, video, climate, weather, security, cameras, and more. Widgets may be further customized and controlled, directly from the touchscreen device.

**Equinox App Widgets Comprehensive Instructions**

Click here to download instructions:

[Vantage Comprehensive Guide to Equinox App](#)

**System Requirements**

Compatible with InFusion Design Center version 3.2 software or higher. For new projects it is recommended that firmware and software be kept to the most current release.

**Installation**

Installation and use of Vantage's Equinox App is designed for today's tablets and smart phones. The App is easy to install. A valid license is needed for *each* equinox device connected to a Vantage System for uninterrupted operation. See table below for license information. Please contact your Vantage dealer for license purchasing options and help.

**Equinox Widget Specifications\***

Description	Specification
Vantage recommends that firmware and software always be kept to the most current version supported by hardware. These are <b>minimum</b> recommendations.	
Android Tablets	Android Ver. 4.0 or higher
Android Phones	Android Ver. 4.0 or higher
Available Free Storage** All Android devices	1- 2 controller system - 50MB Free 3 or more controller system - Over 50MB Free and up
iPad	iOS Ver. 6.0 or higher
iPod	iOS Ver. 6.0 or higher
iPhone	iOS Ver. 6.0 or higher
Available Free Storage** All Apple iOS devices	1- 2 controller system - 50MB Free 3 or more controller system - Over 50MB Free and up
InFusion Design Center	Version 3.2.x or higher

\*Specifications subject to change without notice.

\*\*Free memory storage dependant on system complexity.

**Additional Equinox App Licenses**

Part #	Description
EQ73TB-TI	Equinox App License 1; each Equinox 73 / 41 series station connected adds 1 more license
EQ73TB-TI-II	
EQ41TB-TI	
<b>Additional Equinox App Licenses via Controller SD Cards</b>	
EQ-APP-5	Equinox App License 1-5
EQ-APP-10	Equinox App License 1-10
EQ-APP-X	Equinox App License Unlimited

**Quick Start Steps**

1. Make sure your Vantage System has one or more available Equinox licenses. Configurations for licenses are detailed in the, *Additional Equinox App Licenses*, table above. Please contact your Vantage dealer for licensing options.
2. Place the Equinox license SD Card in the InFusion Controller. It is recommended to replace the existing SD card. Remember to select the option to *Write to Memory Cards* next time (and periodically) the system is programmed from Design Center to completely update the new SD card.
3. Make sure the Design Center project has been programmed with an **Equinox Mobile Passcode**, and an **Equinox Admin PIN**. In Design Center click on *Settings | Project Information | Owner* and fill in the *Equinox Mobile Passcode* and the *Equinox Admin PIN*. After the codes are entered, the system must be programmed or updated. Passcodes are case-sensitive and may consist of letters and numbers, the Admin PIN field must be numbers only. The Equinox App will not be able to run without the *Equinox Mobile Passcode* code and *Profiles* will not be secure without the *Equinox Admin PIN* number.
4. For the Android tablet or phone, download the Vantage Equinox App from Google Play. Search for *Vantage Equinox*. Select Vantage Equinox for Android tablets or Vantage Equinox for Android phones. For the iPad, iPod, or iPhone, download the Vantage Equinox App from the App Store™. Search for *Vantage Equinox*. Install the App as part of the download / selections.
5. Launch the App and follow the on-screen prompts in the *Setup Wizard*.
6. For detailed help continue reading these instructions.
7. **IMPORTANT:** For remote connections to mobile devices, forward **port 41101** to the InFusion controller's IP address.


**Equinox App Setup Wizard Instructions**

*Pre-Install Notes for Mobile Devices:*


- Equinox 73 does not use this setup wizard, they are configured to the system via their internal serial numbers in Design Center.
- A license is required for each mobile device connected - see *Additional Equinox App Licenses* above.

NOTE: Information and screen shot appearances are subject to change, however, instructional updates will be made periodically to maintain accuracy in instructional material.


*Setup Wizard Steps to Connect Mobile Android and iOS Devices*




**Equinox App License**  
Before connecting, the InFusion System must have one available Equinox licenses in order for the App to run without interruption. One additional license is provided for each Equinox 73 station connected to the InFusion System. Multiple license packages are available on Controller SD cards. Proper licensing prevents the, recurring, error shown at the left.



1. Install the App following the portable device's App installation process. Go to Google Play for Android and the Apple Store for iOS devices; search for *Vantage Equinox*.
2. Launch the App and tap the highlighted icon as shown at the left.



NOTE: If the mobile device has already been configured to the system but has been used on another system and or the device's data has been cleared, then after tapping the button in step 2 above, the App will launch. Either message at the left may appear in similar scenarios.  
NOTE: If the data has been cleared on the InFusion Controller, then App should go through the setup wizard steps.

	<p>3. Select the language and then select <i>system</i> in the lower right side of the screen or slide the screen to the left as shown.</p>
	<p>4. Enter the IP address of the InFusion Controller on the InFusion System. NOTE: If the system has multiple controllers, enter the IP address of any controller connected directly to the local network through an Ethernet cable. 5. For <i>remote access</i>* ability, select and enter the <i>remote ip address</i>. *For remote access forward port 41101 to the InFusion controller's IP address in your router's settings. 6. Tap the connect button to connect to the system.</p>
	<p>7. A <i>passcode is required</i>, enter the <i>Equinox Mobile Passcode</i>: entered in Design Center under, <i>Settings   Project Information   Owner</i>. 8. If the passcode is incorrect the system will prompt for the correct passcode until correctly entered. Passcodes are case sensitive and may consist of characters and numbers.</p>
	<p>9. When the correct passcode is entered the Equinox App will automatically configure to the system and, when finished, it will open the <i>profiles</i> page.</p>
	<p>10. Select one of the existing administrative profiles or create a new profile. Select <i>new profile</i> and enter a new profile name from the pop-up keyboard. <i>Tip: Keep profile names short to fit on tablets and smart phones. With few exceptions, new profiles may be created here when the setup wizard is running on a new mobile device. Managing, creating, and deleting profiles is always available, from inside the App, when the App is running.</i></p>
	<p>11. Confirm that the new profile wanted is selected. 12. Tap the lower right side of the screen, or swipe the screen, to continue to the <i>widgets</i> page.</p>
	<p>13. Tap the circle to place or remove the checkmark for each widget wanted. By default they are all selected. 14. Select the grid icon to slide the selected widget up or down in the list to change the order.</p>
	<p>15. Tap the <i>modify</i> button to select a <i>default room</i> and from the pursuing screens select the floor and then the room wanted. The default room selected, in this step, will automatically populate the <i>lighting</i> widget, for the chosen profile, when setup is finished. 16. Select either <i>fahrenheit</i> or <i>celsius</i> for all temperature displays. (default = <i>fahrenheit</i>) 17. Select 12 or 24 hour clock display. (default = 12 hour) 18. Tap the lower right side of the screen, or swipe the screen, to continue to the <i>summary</i> page.</p>
	<p>19. Confirm settings on the summary page. <b>Note:</b> If changes are wanted, tap the lower left or swipe the screen to move back to previous pages. 20. Tap <i>save</i> to conclude the setup wizard.</p>
	<p>21. The Equinox App will connect and finalize configuring. <b>Note (this is not a required step):</b> Tap the menu button , upper right, to see the controller IP address, the station address for Equinox 73 stations, and the forget system option. Tapping on <i>forget system</i>, will cause the screen to forget the controller's IP address. This means the next time the screen is started up, the connection wizard will run and stop at the message screen just below step 2 above as long as the Controller has the Equinox information stored.</p>
	<p>22. The Equinox App should now be running for the first time on the system. 23. Individual widgets may now be used and/or customized as wanted.</p>