



## PASSIVE INFRARED WALL SWITCH SENSOR

PW-301 | [Wattstopper](#)

---

### FEATURES & BENEFITS

The PW-301 passive infrared (PIR) wall switch sensor can turn lights OFF and ON based on occupancy. It is characterized by high sensitivity to small and large movements, appealing aesthetics, and a variety of features.

- High sensitivity and dense coverage for exceptional performance
- Color-matched lens and low profile for appealing design
- Defaults to Manual-ON operation for maximum energy savings
- Optional neutral connection with break off tab to expose neutral terminals
- 120/277VAC and 347VAC models
- Allows multi-way control from one of up to four control locations

---

### SPECIFICATIONS

#### ADDITIONAL INFORMATION

##### MODELS

Product Number: PW-301-W, PW-301-LA, PW-301-I, PW-301-G, PW-301-B, PW-301-R, PW-301-347-W, PW-301-347-LA, PW-301-347-I, PW-301-347-G, PW-301-347-B, PW-301-347-R

#### GENERAL INFO

Typical Applications: Small Office, Small Conference Room, Lunch/Break Rooms

Special Features: Multi-way Dual Relay

#### TECHNICAL INFORMATION

IR Range On Axis: 525 SqFt

LightOutput 1FCD: Automatic On/Off, Manual On/Off

Load: 1-1000 W, 1/ hp

Response Time: 5 to 30 minutes

Volts: 120/277VAC, 50/60Hz, 347VAC