



## PHASING OUT - PASSIVE INFRARED DUAL RELAY WALL SWITCH OCCUPANCY SENSOR

PW-201 | [Wattstopper](#)

### FEATURES & BENEFITS

The PW-201 passive infrared (PIR) wall switch sensor turns lights ON and OFF based on occupancy. It contains two relays for controlling two independent lighting loads or circuits, and a variety of features. This product is phasing out. The replacement product is PW-302.



- High sensitivity and dense coverage for exceptional performance
- Two relays for control of two separate lighting loads or circuits
- Color-matched lens and low profile for appealing design
- Selectable operation, walk-through, test and presentation modes for increased energy savings and convenience
- Defaults to Auto-ON to 50% operation for maximum energy savings
- Includes neutral wire to meet NEC 2011 code

### SPECIFICATIONS

#### ADDITIONAL INFORMATION

##### MODELS

Product Number: PW-201-W, PW-201-LA, PW-201-I, PW-201-G, PW-201-B

##### REPLACEMENT PRODUCT:

PW-302

#### GENERAL INFO

Typical Applications: Small offices, small conference rooms, individual restrooms, lunch/break rooms

Special Features: Dual Relay

#### TECHNICAL INFORMATION

IR Range On Axis: 525 SqFt

LightOutput 1FCD: Automatic On/Off, Manual On/Off  
Load: 0-1200 W, 1/6 hp  
Volts: 120/277VAC, 50/60 Hz