



**Wattstopper**  
**Discontinued - Resi PIR VAC Sens, 2-wire, Blk**  
Part No. CS-50-B



The CS-50 Passive Infrared (PIR) Vacancy Sensor provides automatic shutoff for single-pole lighting control applications. It is engineered to comply with specific provisions of California's Title 24-2013 energy code.

## Features & Benefits

Collection consolidated to white option

LED status indicator

Two-wire sensor; no neutral connection

Manual-on/automatic-off control

Adjustable time delay

## Specifications

### General Info

|                    |             |                         |  |
|--------------------|-------------|-------------------------|--|
| Product Line       | Wattstopper | Replaced by Part Number | CS-50-W  |
| Color              | Black       | UPC Number              | 754182926947                                   |
| Country Of Origin  | China       | Features                | Indicator Lights, IR (Infrared), Motion Sensor |
| Application Sector | Commercial  | Warranty Type           | 5-Year   |

### Dimensions

|                   |            |                   |           |
|-------------------|------------|-------------------|-----------|
| Product Width US  | 1.7 in     | Product Weight US | 0.2095 lb |
| Product Volume US | 11.1 cu in | Product Depth US  | 1.8 in    |
| Product Height US | 4.2 in     |                   |           |

### Additional Information

---

|                |     |          |     |
|----------------|-----|----------|-----|
| RoHS Compliant | Yes | Security | Yes |
|----------------|-----|----------|-----|

---

### Technical Information

---

|             |         |                 |   |
|-------------|---------|-----------------|---|
| Sensor Type | Vacancy | Number of Gangs | 1 |
|-------------|---------|-----------------|---|

---

|                   |   |          |     |
|-------------------|---|----------|-----|
| Number of Buttons | 1 | Amperage | 5 A |
|-------------------|---|----------|-----|

---

|                   |                        |         |       |
|-------------------|------------------------|---------|-------|
| Sensor Technology | Passive Infrared (PIR) | Wattage | 600 W |
|-------------------|------------------------|---------|-------|

---

|                 |       |
|-----------------|-------|
| Connection Type | Wired |
|-----------------|-------|

---