



Wattstopper
Discontinued - PIR Dimmable Wall Switch Occupancy Sensor, 120/277V, Black
Part No. PW-100D-B



The PW-100D and PW-101D passive infrared (PIR) dimmable wall switch sensors can turn light OFF and ON based on occupancy. It is characterized by high sensitivity to small and large movements, appealing aesthetics, and a variety of features.

Features & Benefits

High sensitivity and dense coverage for exceptional performance	Defaults to Manual-ON operation for maximum energy savings
Color-matched lens and low profile for appealing design	Pushbutton dimming control and optional locked preset level for many lighting types
Selectable operation, walk-through, test and presentation modes for increased energy savings and convenience	Part of a comprehensive line of PIR, Ultrasonic and Dual Technology wall switch sensors
Part of a comprehensive line of PIR, Ultrasonic and Dual Technology wall switch sensors	Detection Signature Processing eliminates false triggers and provides immunity to RFI and EMI
Vandal resistant lens combines precise coverage with durability	Selectable walk-through mode turns lights off three minutes after the room is initially occupied if no motion is detected after the first 30 seconds
In automatic mode, sensor returns automatically to Auto-ON after lights are turned off manually; ideal for presentations	Selectable audible and/or visual alerts for impending shutoff
2-wire and 3-wire models available for applications with or without neutral wire	

Specifications

General Info

Product Line	Wattstopper	Replaced by Part Number	PW-101D-B
Color	Black	UPC Number	754182930838
Country Of Origin	China	Features	IR (Infrared), Motion Sensor

Switch Type	Motion Sensor	Application Sector	Commercial
Warranty Type	5-Year		
Dimensions			
Product Width US	1.8 in	Product Weight US	0.25 lb
Product Volume US	36.0 cu in	Product Depth US	1.8 in
Product Height US	4.1 in		
Additional Information			
Product Environmental Profile	Yes		
Technical Information			
Response Frequency	50/60 Hz	Sensor Type	Occupancy
Number of Buttons	1	Amperage	4.3 A
Sensor Technology	Passive Infrared (PIR)	Indicator	LED Light
Requires Neutral Wire	No	Wattage	1200 W
Connection Type	Wired		