



## Wattstopper Discontinued - PIR Wall Switch Occupancy Sensor, 120/277V, Red Part No. PW-200-R



The PW-200 passive infrared (PIR) wall switch sensor turns lights ON and OFF based on occupancy. It contains two relays for controlling two independent lighting loads or circuits, and a variety of features.

### Features & Benefits

High sensitivity and dense coverage for exceptional performance

Color-matched lens and low profile for appealing design

Defaults to Auto-ON to 50% operation for maximum energy savings

Two relays for control of two separate lighting loads or circuits

Selectable operation, walk-through, test and presentation modes for increased energy savings and convenience

Defaults to Auto-ON to 50% operation for maximum energy savings

### Specifications

#### General Info

Product Line	Wattstopper	Replaced by Part Number	PW-302-R
Color	Red	UPC Number	754182934430
Country Of Origin	China	Features	IR (Infrared), Motion Sensor
Switch Type	Motion Sensor	Application Sector	Commercial
Warranty Type	5-Year		

#### Dimensions

Product Width US	1.8 in	Product Weight US	0.3 lb
Product Volume US	35.1 cu in	Product Depth US	1.8 in
Product Height US	4.5 in		

---

## Additional Information

---

Product Environmental Profile    Yes

---

## Technical Information

---

Response Frequency	50/60 Hz	Sensor Type	Occupancy
--------------------	----------	-------------	-----------

---

Number of Buttons	2	Amperage	4.3 A
-------------------	---	----------	-------

---

Sensor Technology	Passive Infrared (PIR)	Indicator	LED Light
-------------------	------------------------	-----------	-----------

---

Requires Neutral Wire	No	Wattage	1200 W
-----------------------	----	---------	--------

---

Connection Type	Wired
-----------------	-------

---