Wattstopper

PIR Wall Switch Occupancy Sensor, 120/277V, Ivory

Part No. PW-302-I

The PW-302 passive infrared (PIR) wall switch sensor turns lights ON and OFF based on occupancy. It contains two relays for controlling two independent lighting loads or circuits, and a variety of features.

Features & Benefits

- High sensitivity and dense coverage for exceptional performance
- Defaults to Auto-ON to 50% operation for maximum energy savings
- 120/240/277 VAC and 347 VAC models
- Two relays for control of two separate lighting loads or circuits
- Optional neutral connection with break off tab to expose neutral terminals
- Allows multi-way control from one of up to four control locations

Specifications

General Info

Product Line	Wattstopper	Color	Ivory
UPC Number	754182935291	Country Of Origin	China
Product Series	PW-300	Features	Adjustable Time Delay, Indicator Lights, Light Level Sensor, Sensitivity Adjustment, Vandal Resistant Lens
Switch Type	Motion Sensor	Installation Location	Wall
Included	Sensor Mask	Application Sector	Commercial

Standard	UL, cUL	Warranty Type	5-Year
Type	Sensor, Switch		

Dimensions

Product Width US	1.75 in	Product Weight US	0.3 lb
Product Volume US	35.1 cu in	Product Depth US	1.81 in
Product Height US	4.1 in		

Additional Information

RoHS Compliant	Yes	DesignLights Consortium Qualified System	Yes
Security	Yes		

Technical Information

Has Battery	No	Number of Connections	5
Sensor Coverage Pattern	180 deg	Sensor Type	Occupancy
Sensor Mounting Height	4 ft	Number of Buttons	2
Amperage	4.3 A	Number of Rockers	0
Sensor Technology	Passive Infrared (PIR)	Input Voltage	120/240/277 VAC
Requires Neutral Wire	No	Line Frequency	50 Hz, 60 Hz
Wattage	1200 W	Mounting Type	In-Wall
On Function	Selectable Auto/Manual	Sensing Range	Major motion 35 x 30 ft,Minor motion 20 x 15 ft
Wire Connection Type	Flying Leads		