



The PW-302 passive infrared (PIR) wall switch sensor turns lights ON and OFF based on occupancy.

## Features & Benefits

Defaults to Auto-ON to 50% operation for maximum energy savings

120/240/277 VAC and 347 VAC models

High sensitivity and dense coverage for exceptional performance

Optional neutral connection with break off tab to expose neutral terminals

Allows multi-way control from one of up to four control locations

Two relays for control of two separate lighting loads or circuits

## Specifications

### General Info

Product Line	Pass & Seymour	Color	Gray
Finish	Matte	UPC Number	754182935284
Country Of Origin	China	Features	IR (Infrared), Motion Sensor
Switch Type	Motion Sensor	Application Sector	Commercial
Type	Switch		

### Dimensions

Product Width US	1.75 in	Product Depth US	1.81 in
Product Height US	2.73 in	Product Length US	2.73 in

### Technical Information

Seismic Tested	No	Response Frequency	60 Hz
Sensor Type	Occupancy	Number of Buttons	2
Number of Poles	Multi-Location	Wire Size	#14 - #10 AWG
Requires Neutral Wire	No	Indoor/Outdoor	Indoor
Wattage	1200 W	Mounting Type	Box
Voltage	120 to 277 V	Connection Type	Wired