



**Wattstopper**  
**PIR Wall Switch Occupancy Sensor**  
Part No. WS-301-I-U



The WS-301 Passive Infrared (PIR) Wall Switch Sensor turns lighting or fan loads on and off based on occupancy and ambient light level. The sensor replaces existing wall switches and fits behind a standard decorator wall plate.

## Features & Benefits

Defaults to Manual-ON operation for maximum energy savings	180° coverage, maximum of 900 ft <sup>2</sup>
Shallow (1"") back housing and flying leads for easy installation	Built-in light level sensor
Optional neutral connection with break off tab to expose neutral terminals	120/240/277 VAC and 347 VAC models
Button provides positive tactile feedback	

## Specifications

### General Info

Product Line	Wattstopper	Color	Ivory
UPC Number	754182938551	Country Of Origin	United States

### Technical Information

Sensor Type	Occupancy	Amperage	4.3 A
Wattage	1200 W	Voltage	120/277 V