AD [TH, TP] RIWHC

In-Wall RF Scene Controller

What This Product Does

The RF Smart Lighting Control system provides a wireless lighting solution for today's integrated home. With a system maximum of (100) end-points, this solution can effortlessly scale for any project.

The Scene Controller is an in-wall keypad that allows for users to trigger 4 preconfigured lighting scenes.

Features

- **Ultra-reliable** with Legrand's patented Radio Frequency technology
- **Easy installation** using existing electrical wiring
- **Simple setup** and device pairing
- **Complete control** via Lighting Control app, Amazon Alexa or the Google Assistant
- **Seamless integration** with IP drivers for Control4, URC, RTI, Elan, and Crestron
- **Convenient grouping** for single-touch control of customized lighting scenes
- **Effortless automation** by time of day or by predetermined preferences
- **Flawless fit and finish** as part of the adorne® Collection

Part of the adorne® *collection*

About the Collection

The adorne® Collection by Legrand combines the world's most innovative light switches and charging solutions with an array of stylish and custom finishes. From ordinary to extraordinary, inside and out - welcome to a brighter home.

AS**THRIWHC-XX Technical Specifications

General Information	
Interfaces Available (**)	TP = SofTap, TH = Touch
Colors Available (xx)	W1 = White, M1 = Magnesium, G1 = Graphite

Product Information	
Product Dimensions	1.8"D x 4.2"H x 4.2"W
Weight	0.32 lbs
Unit Package Dimensions	2.8"D x 6.1"H x 3.8"W
Case Package Quantity	8
Case Package Dimensions	4.125"D x 6.5"H x 17.875"W

Technical Information	
Radio	900MHz Top Dog™ Radio Frequency
System Range	100ft between devices (expands up to 300ft between devices when used with (2) MRR2G)
AC Voltage Input	120V
Frequency	60Hz
Terminal	Terminals accommodate #12 and #14 AWG stranded and copper wire.
Humidity	0-80% relative humidity, non-condensing
Operating Temperature	32°~122°F (0°~50°C)

COMPATIBILITY

- Works with Alexa and the Google Assistant
- IP-based drivers for seamless integration with Control4, Elan, RTI and URC
- Serial-based driver for Crestron

COMPLIANCE

- cULus Listed
- RoHS Compliant
- FCC Class B Part 15

SYSTEM REQUIREMENTS

- LC7001 (Whole-House Lighting Controller)
- Neutral wire required
- adorne® Wall Plate (not included)

WARRANTY

- One-year limited warranty

USA 866.977.3901 • **CANADA** 877.345.4329
av.resi.sales.operations@legrand.com
legrandav.com ©2019 Legrand AV Inc.